

Receiver Model	Description	Ch	Stereo/ Mono	XLR	XLR Signal Out	RCA	Line Signal Out	Freq Res (Hz)	Noise Gate	Dual Diversity	Use With
PAR900M	PRO Series Wireless Audio Receiver	24	Mono	x	3.5Vpp	x	1.5Vpp	30-20k	x	x	PAT900, AT900-24DZ

Transmitter Model	Description	Ch	Stereo/ Mono	XLR	XLR Input Z	RCA	Line Input Z	Freq Res (Hz)	Mic Input	Remote Antenna	Use With
PAT900	Pro Audio Transmitter, Mono	24	Mono	x	200k	x	50k	30-20k	x		PAR900M
AT900-24DZ	Audio Transmitter with Remote Outdoor Antenna	24	Mono			x	10k	50-15k		x	PAR900M
AT900-24DY	Audio Transmitter with Remote Indoor Antenna	24	Mono			x	10k	50-15k		x	PAR900M

All products above operate at 902 to 928 MHz.

All products above come with power adapters.

Max. Line-of-Sight Range for all products are 750 feet with included antennas. Higher gain antennas are also available.

These are analog products so there is no latency.

Optional Directional Antennas for use on Receivers

Model	Description	Size (inches)	Elements	Beam width
FP915-5	Flat Panel, 5dBd	8 x 8 x 1 in		65 deg
Y915-8	Yagi, 8 dBd	21"	5	55 deg
Y915-10	Yagi, 10 dBd	26"	7	50 deg
FB35T900	Vertical, Omni-Directional, 6-dB, N Female	22"	1	360 deg

First 3 Antennas above have 3' RG58 cable with BNC male Connector.

Use with amplified speakers or separate amplifier(s) and speakers.



PAR900 Pro Audio Receiver



PAT900 Pro Audio Transmitter



Remote Outdoor Transmit Antenna